



100 Series™ Low-Profile Plug-in Smoke Detectors



System Sensor 100 Series Plug-in Smoke Detectors offer superb performance and reliability in a profile which is just 2" (5.1 cm) deep.

Features

- Sleek, low-profile design
- Compatible with 400 Series product
- Two LEDs blink in standby, providing 360° visibility
- Broad range of adapter bases available with built-in shorting spring
- Hand-held sensitivity reader available

Model 2151 (photoelectric sensor) and model 2151T (photoelectric sensor with thermal) can be used with a variety of adapter bases in several wiring configurations and voltages. Other features include: low current draw, stable performance in high air velocities, built-in tamper resistant base design, remote LED option, removable cover and built-in test switch.

The 100 series is designed to meet the performance criteria designated by UL. The sensing chamber is sealed against back pressure air flow. The chamber top is covered by a one piece molded screen which minimizes the entry of dirt and insects. This screen can be removed for cleaning. Additional key features include a variety of mounting bases and a full line of accessories.

All 100 Series photoelectric smoke detectors contain a unique optical sensing chamber designed to sense smoke particles produced by a wide range of combustion sources. A custom integrated circuit incorporates signal processing to reduce false alarms.

Model 2151 photoelectric detector's unique optical sensing chamber is engineered to sense smoke by a wide range of combustion sources. Dual electronic thermistors add 135°F fixed temperature thermal sensing on model 2151T.

Agency Listings



100 Series Plug-in Smoke Detector Specifications

Operating Voltage/Alarm Current	See Adapter Base Selection Guide following
Standby Current	120 μ A Standby (when mounted in a B110LP base)
Sensitivity	1 – 3.18%/ft.
Height	2.0" in B401
Diameter	4.1" installed in B401; 6.2" installed in B110LP
Shipping Weight	5.2 oz
Construction	Flame retardant thermoplastic
Temperature	Photo: 32°F to 120°F (0° to 49°C); Photo/thermal: 32°F to 100°F (0° to 38°C)
UL Listed Velocity Range	Photo: 0 – 3000 fpm (0 – 15.2 m/s)
Humidity Range	10% – 93% RH non-condensing
Smoke Detector Spacing	On smooth ceilings (as defined in NFPA 72), spacing of 30 feet (900 sq. ft.) may be used as a guide. Other spacing may be used depending on ceiling height, high air movements, and other conditions or response requirements.

Adapter Base Selection Guide					
Base Model Number	Loop Type	Current Limit Resistor	Contact Type	Nominal Voltage	Current Draw on Alarm (mA)
B110LP	2-wire*	No	—	12/24VDC	10–130 [†]
B110RLP	2-wire*	Yes	—	24VDC	10–62
B112LP	4-wire	Yes	Form A&C	24VDC	17–36
B114LP	4-wire	Yes	Form A&C + A Supervisory	120VAC	75 mA AC Max
B116LP	2-wire*	No	Form C	24VDC	20–100 [†]
B401 ^{††}	2-wire*	No	—	12/24VDC	10–130 [†]

*Functionality contingent on panel compatibility †Must be limited by control panel ††Flangeless base

Relay Contact Ratings:	Resistive or Inductive (60% power factor) load.
Form A:	2.0A at 30 VAC/DC
Form C:	0.6A at 110VDC, 2.0A at 30VDC 1.0A at 125VAC, 2.0A at 30VAC

Junction Box Selection Guide*							
Base Model Number	Single Gang	3½" Octagon	4" Octagon	4" Square	50 mm	60 mm	75 mm
B401	No	No	No	No	Yes	Yes	No
B110LP/RLP	Yes	Yes	Yes	Yes	No	No	No
B112LP/B116LP	Yes	Yes	Yes	Yes	Yes	Yes	Yes
B114LP	No	No	Yes	Yes	No	No	No

*Box depth contingent on base and wire size. Refer to National Electrical Code or local applicable codes for appropriate recommendations.

Ordering Information

Part No.	Description
2151	Low-profile photoelectric detector. Must be mounted to one of the B100 Series or B400 Series bases listed in the Adapter Base Selection Guide.
2151T	Low-profile photoelectric detector with thermal. Must be mounted to one of the B100 Series or B400 Series bases listed in the Adapter Base Selection Guide.

Accessories	
F110	Accessory Flange Ring for 6" Base
RA100Z	Remote annunciator for 2 or 4 wire systems, 3–32V. Fits standard single gang electrical box.
SENS-RDR	Hand-held sensitivity reader.
SMB600	Surface mounting kit (flanged)
EOLR-1	End of line relay for power supervision, 12/24 VDC systems.
M02-04-01	Test magnet.
M02-09-00	Test magnet with 32" telescoping handle.
XR-2B	Detector removal tool. Allows installation and/or removal of 100 Series detector heads from base in high ceiling installations when used with XP-4.
XP-4	Extension pole for XR-2B. Comes in three 5 ft. sections.
C58-227-01	Replacement dust cover for 100 Series smoke detectors.



3825 Ohio Avenue • St. Charles, IL 60174
Phone: 800-SENSOR2 • Fax: 630-377-6495

©2011 System Sensor.
Product specifications subject to change without notice. Visit systemsensor.com for current product information, including the latest version of this data sheet.
A05-0182-015 • 11/11 • #2709